Product Specification Sheet
WNC-NP
Wireless Emergency Call Pendant



WNC-NP
Wireless Emergency Call Pendant

The WNC-NP is a 900MHz spread specturm, waterproof RF/RFID mini-transmitter with necklace attachment, push for help button, magnetic call cancel and dual color LED with alarm in red and reset in green. Weighing in at eight tenths of an ounce, the WNC-NP features a waterproof housing that protects the pendant when worn in the shower, bathtub, or other enviornments where the pendant may be submerged. It is not recommended for use by divers or in pools or spas where chlorine and other chemiclas may shorten the life expectancy. It features easy single button activation and a raised bump for use at night or by the visually impaired. Calls are magnetically reset with the tool which provides a reset magnet on one end and battery door tool on the other end.

Architects' and Engineers' Specifications

A BEC personal mini transmitter part number WNC-NP shall be available. This 900 MHZ RF/RFID unit shall include a transmit button for push button calling, a red transmit LED indicator that blinks to show a call being placed and a green LED indicator that blinks to show "Re-Set" when alarm is cancelled. A one secound depression of the transmit button shall result in the alarm signal being transmitted multiple times and the red LED will blink. The unit shall be water resistant and include a plastic necklace chain and battery. It shall have a non-Volatile memory and supervised for operation and battery voltage.

Specifications

- **Dimensions w/wrist strap:**
  Height: 2.04"
  Width: 1.54"
  Depth: 0.62"
  Weight: 8 oz
- **Battery:** 3.0V Lithium CR2450
- **Battery Life:** 1-2 years (fully supervised)
- **Supervisory** Transmission: 1 Hour

System Components

Server 2: Video Display Console
MV500: Desk Console Receiver
MV200 PLUS: Desk Console Receiver
WNC-CC: Locator Beacon
WNC-RPH: Repeater/ Locator-High power
WNC-RP: Repeater/ Locator

Features

- Reliable 900 MHz spread frequency transmission
- Two color LED for easy identification of alarm and reset
- Simple push button calling.
- Magnetic "Re-Set" for alarm cancellation
- Alarm signals are transmitted multiple times
- Fully supervised for operation and battery

Toll-Free: 888.556.3998
Phone: 716.689.0871
Address: 5225 SHERIDAN DR STE 110,
GEORGETOWN SQUARE, WILLIAMSVILLE NY 14221-4952
E-mail: support@becsolutionsllc.com